

# FP6134

# 600mA Low Dropout Linear Regulator with Shutdown

### Description

The FP6134 is a low dropout, positive linear regulator with very low quiescent current. The FP6134 can supply 600mA output current with low dropout voltage at about 600mV. The BP pin with a  $0.1\mu$ F bypass capacitor can help reducing the output noise level. The shutdown function can provide remote control for the external signal to decide the on/off state of FP6134. With a logic high level at SHDN pin, the device is in the on state, and vice versa.

The FP6134 regulator is able to operate with output capacitors as small as  $1\mu$ F for stability. The FP6134 also offers the on chip thermal shutdown feature to provide protection against overload or any condition when the ambient temperature exceeds the maximum junction temperature.

The FP6134 offers high precision output voltage of  $\pm 2\%$ . It is available in fixed output voltages including 1.5V, 1.8V, 2.5V, 2.8V, 3.0V, 3.1V and 3.3V.

The FP6134 is housed in low-profile and space-saving 5-lead SOT-23-5 package.

### **Pin Assignments**

S5 Package (SOT-23-5)



Figure 1. Pin Assignment of FP6134

#### SOT-23-5 Marking

Part Number	Product Code	Part Number	Product Code
FP6134-15S5P	Fi	FP6134-28S5G	Fn=
FP6134-15S5G	Fi=	FP6134-30S5P	Fr
FP6134-18S5P	Fk	FP6134-30S5G	Fr=
FP6134-18S5G	Fk=	FP6134-31S5P	Fu
FP6134-25S5P	Fm	FP6134-31S5G	Fu=
FP6134-25S5G	Fm=	FP6134-33S5P	Fs
FP6134-28S5P	Fn	FP6134-33S5G	Fs=

#### **Features**

- Low Dropout Voltage of 600mV at 600mA
- High Ripple Rejection at 60dB
- Guaranteed 600mA Output Current
- Very Low Quiescent Current at 30µA
- Max. ±2% Output Voltage Accuracy
- Needs Only 1µF Capacitor for Stability
- Thermal Shutdown Protection
- Current Limit Protection
- Active Low Shutdown Control
- Low-ESR Ceramic Capacitor for Output Stability.
- Tiny package: SOT-23-5
- RoHS Compliant

### Applications

- DSC
- Wireless Device
- LCD Module
- Battery Power System
- Card Reader
- PDA

### **Ordering Information**



Note1: Please consult Fitipower sales office or authorized distributors for availability of special output voltages.



# **Typical Application Circuit**



Figure 2. Typical Application Circuit of FP6134

Note 2 : To prevent oscillation, it is recommended to use minimum 1µF X7R or X5R dielectric capacitors if ceramics are used as input/output capacitors.

### **Functional Pin Description**

Pin Name	Pin No.	Pin Function
VIN	1	Power is supplied to this device from this pin which requires an input filter capacitor. In general, the input capacitor in the range of $1\mu$ F to $10\mu$ F is sufficient.
GND	2	Common ground pin
SHDN	3	Pull this pin high to enable IC, and pull this pin low to shutdown IC
BP	4	Reference Noise Bypass
VOUT	5	The output supplies power to loads. The output capacitor is required to prevent output voltage from oscillation. The FP6134 is stable with an output capacitor which is 1µF or greater. The larger output capacitor will be required for application with larger load transients. The large output capacitor could reduce output noise, improve stability and PSRR.



# **Block Diagram**



Figure 3. Block Diagram of FP6134

## **Absolute Maximum Ratings**

• Supply Input Voltage (V <sub>IN</sub> )	+6V
• Power Dissipation SOT-23 (P <sub>D</sub> )	+0.4W
<ul> <li>Package Thermal Resistance SOT-23 (θ<sub>JA</sub>)</li> </ul>	+250°C/W
• Maximum Junction Temperature (T <sub>J</sub> )	+150ºC
• Storage Temperature Range (T <sub>S</sub> )	-65°C to +150°C
• Lead Temperature (Soldering, 10 sec.) (T <sub>LEAD</sub> )	+260ºC
Note : Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage	to the device.

# **Recommended Operating Conditions**

Input Voltage (V <sub>IN</sub> )	+2.8V to +5.5V
• Operating Temperature Range (T <sub>OPR</sub> )	



### **Electrical Characteristics**

( $V_{IN}=V_{OUT}+1V$  or  $V_{IN}=2.8V$  whichever is greater,  $\overline{SHDN}$  pin connected to  $V_{IN}$ ,  $C_{IN}=1\mu$ F,  $C_{OUT}=1\mu$ F,  $T_A=25^{\circ}$ C, unless otherwise specified)

Parameter	Symbol	Conditions		Min	Тур	Max	Unit
Current Limit	I <sub>LIMIT</sub>	$R_{Load}=1\Omega$		600			mA
Quiescent Current	ΙQ	I <sub>O</sub> = 0mA			30	50	μA
Standby Current	I <sub>STBY</sub>	V <sub>IN</sub> =2.8~5V	, Output Off			0.1	μA
Output Voltage Accuracy	ΔV <sub>OUT</sub>	I <sub>O</sub> = 1mA		-2		+2	%
		I <sub>0</sub> =600mA	V <sub>OUT</sub> =1.5V		1550	1690	-
			V <sub>OUT</sub> =1.8V		1300	1420	
Dropout Voltage (Note 4)	V <sub>DROP</sub>		V <sub>OUT</sub> =2.5V		800	900	mV
			V <sub>OUT</sub> =3.0V		650	730	-
			V <sub>OUT</sub> =3.3V		600	670	
Line Regulation	V <sub>LINE</sub>	I <sub>O</sub> =1mA, V <sub>IN</sub> =V <sub>OUT</sub> +1V to 5V			1	5	mV
Load Regulation (Note 5)	$\Delta V_{LOAD}$	I <sub>O</sub> =0mA to 600mA			13	50	mV
Ripple Rejection (Note6)	PSRR	V <sub>IN</sub> =V <sub>OUT</sub> +1V , C <sub>BP</sub> =0.1μF f <sub>RIPPLE</sub> = 120Hz, C <sub>OUT</sub> = 1μF			60		dB
Temperature Coefficient (Note 6)	T.C.	I <sub>OUT</sub> = 1mA, V <sub>IN</sub> = 5V			50		ppm/⁰C
Thermal Shutdown	T <sub>SD</sub>				160		٥C
Temperature (Note 6)	$\Delta T_{SD}$	Hysteresis			25		٥C
Shutdown Pin Current	I <sub>SHDN</sub>					0.1	μA
Noise Bypass Terminal Voltage (Note 6)	$V_{REF}$				1.23		V
	$V_{\overline{SHDN}(ON)}$	Output ON		1.4			V
Shuldown Pin Vollage	$V_{\overline{SHDN}(OFF)}$	Output OFF				0.4	V
Shutdown Exit Delay Time (Note 6)	ΔΤ	С <sub>вР</sub> =0.1µF, С <sub>ОUТ</sub> =1µF, I <sub>OUT</sub> =30mA			300		μs

Note 4: The dropout voltage is defined as VIN-VOUT, which is measured when VOUT drops 2% of its normal value with the specified output current.

Note 5: Load regulation and dropout voltage are measured at a constant junction temperature by using a 40ms low duty cycle current pulse. Note 6: Guarantee by design.



# FP6134

# **Typical Performance Curves**











Vout=3.3V Cin=1uF

Figure 7. Quiescent Current vs. Temperature



Figure 9. Dropout Voltage vs. Temperature (V<sub>OUT</sub>=2.8V)



# FP6134



## **Typical Performance Curves (Continued)**













FP6134-2.2-APR-2014



#### **Application Information**

The FP6134 is a low dropout linear regulator that could provide 600mA output current at dropout voltage about 600mV. Current limit and on chip thermal shutdown features provide protection against overload or any condition when the ambient temperature exceeds the maximum junction temperature.

#### **Output and Input Capacitor**

The FP6134 regulator is designed to be stable with a wide range of output capacitors. The ESR of the output capacitor affects stability. Larger value of the output capacitor decreases the peak deviations and improves transient response for larger current changes.

The capacitor types (aluminum, ceramic, and tantalum) have different characterizations such as temperature and voltage coefficients. All ceramic capacitors are manufactured with a variety of dielectrics, each with different behavior across temperature and applications. Common dielectrics used are X5R, X7R and Y5V. It is recommended to use 1µF to 10µF X5R or X7R dielectric ceramic capacitors with  $30m\Omega$  to  $50m\Omega$  ESR range between device outputs and ground for stability. The FP6134 is designed to be stable with low ESR ceramic capacitors and higher values of capacitors. and ESR could improve output stability. The ESR of output capacitor is very important because it generates a zero to provide phase lead for loop stability.

There are no requirements for the ESR on the input capacitor, but its voltage and temperature coefficient have to be considered for device application environment.

#### **Protection Features**

In order to prevent overloading or thermal condition from damaging the device, FP6134 has internal thermal and current limit functions designed to protect the device. It will rapidly shut off PMOS pass element during over temperature condition.

#### **Thermal Consideration**

The power handling capability of the device will be limited by allowable operation junction temperature (125°C). The power dissipated by the device will be estimated by  $P_D = I_{OUT} \times (V_{IN}-V_{OUT})$ . The power dissipation should be lower than the maximum power dissipation listed in "Absolute Maximum Ratings" section.

#### Shutdown Operation

The FP6134 is shutdown by pulling the SHDN input low and turned on by driving the SHDN high. If this function is not used, the SHDN input should be tied to VIN to keep the regulator on all the time (the SHDN must not be left floating).



# **Outline Information**







SYMBOLS	DIMENSION IN MILLIMETER			
UNIT	MIN	MAX		
А	0.90	1.45		
A1	0.00	0.15		
A2	0.90	1.30		
В	0.30	0.50		
D	2.80	3.00		
E	2.60	3.00		
E1	1.50	1.70		
е	0.90	1.00		
e1	1.80	2.00		
L	0.30	0.60		

Note : Followed From JEDEC MO-178-C.



### **Carrier Dimensions**



	=:
W2-	

Tape Size	Pocket Pitch	Reel Size (A)		Reel Size (A)		Reel Width	Empty Ca∨ity	Units per Reel
(W1) mm	(P) mm	in	mm	(W2) mm	Length mm			
8	4	7	180	8.4	300~1000	3,000		